

WAC-2D2T-ENC
WAC-4D4T-ENC
WAC-4D8T-ENC
WAC-8D8T-ENC



Description:

WAC Access Controllers are designed to be self-contained controllers ideally suited for small and medium sized companies. Packed with rich features, this product takes care of a variety of control and automation functions in addition to basic access control requirements of any facility.

The models have been designed for specific access requirements in any facility such as access by card and exit by push button. Based on the needs on site, the designer can choose from available models capable of controlling access to 1, 2, 4 or 8 doors (per panel).

The controllers communicate through the traditional RS485 Bus or TCP/IP. The controllers are capable of using industry standard 26-72 bit Wiegand readers as well as other related technologies.

The 2 Door controller can directly power up to 2 door strikes, when using maglocks an additional power supply is needed. 4 door or 8 door controllers require an additional power supply to operate maglocks and/or strikes.

Note local fire and building codes may apply when using maglocks.

Lockable cabinet and control board power supply included with the Access Control Kits.



WatchNET provides ease of installation with a wiring diagram printed on the cabinet door.

Weatherproof and IP rated controller cabinets are available.

Features:

- Supports RS232/RS485/TCP/IP
- Cards holder capacity: 30,000 / 100,000 (online mode)
- Transactions storage: up to 270,000
- Supports keypad readers for requiring a PIN when entering a door
- Supports up to 500 temporary cards with security settings
- Up to 365 holidays
- 15 Time Zones for each door
- 24 sets of Flow Control
- Local and Global Anti-Pass back
- Programmable Door Status
- Always Closed (Can be opened by Supervisor cards only)
- Multiple types of Events
- Data can be kept for 180 days without power
- CE, FCC, RoHS approval



Model	WAC 2D2T ENC	WAC 4D4T ENC	WAC 4D8T ENC	WAC 8D8T ENC
				
Description	2 Door 2 Reader	4 Door 4 Reader	4 Door 8 Reader (IN/OUT)	8 Door 8 Reader
Number of Readers	2	4	8	8
Card holders	30,000 / 100,000 (online mode)			
Memorized events	270,000	270,000	270,000	270,000
Built-in inputs	4	2	4	0
Built-in outputs	4	6	8	8
Exit button Inputs	2	4	4	8
PCB size	17cm x 13cm / 6.7" x 5.1"			
PCB weight	0.5 Kg			
CPU	32 bits of ARM, 2 watch-dogs			
Memory	32 KB ROM / 512KB SRAM			
Card/Transactions capacity	30,000 card holders, 270,000 off line event buffer, Unlimited transactions (on line)			
Reader	Supports Wiegand 24 to 72 bits (Fingerprint reader, EM/Mifare reader) Supports WatchNET and other readers with Wiegand Protocol			
Communication	TCP/IP 127 controllers for each RS485 Up to 1,200 m for each RS485 Communication speed:19,200/9,600/4,800 1,1,n			
Input/output port	RJ45 Socket for Plug & Play connection of readers Dry door relay/extension relays output, 5A Exit Buttons, Door Lock Sensors, Extension Inputs			
Protection circuit	Protects the board from over voltage and short circuit			
Auto-test	Yes			
Led indicator light	Yellow: power; red and green: communication			
Power	12VDC (±30%), 300mA Auto volt 100 to 240VAC 50 / 60Hz with power supply			
Work environment	Temperature: -40°C ~ 70°C / 40° F ~ +158° F / Humidity: 0 to 90%			
Package	Metal housing with power supply			
Dimension (mm)	40.3cm x 38.4cm x 7.2 cm / 15.8" x 15.1" x 2.8"			
Weight	4.5kg / 9.92lb			

All logos & trade marks represent the registered users only. All rights reserved.
All product specifications on this brochure are subject to change without notice.

CANADA:
351 Ferrier Street, Unit 5
Markham, ON L3R 5Z2
Toll Free: 1-866-843-6865
Tel: 416-410-6865
Fax: 1-866-331-3341

USA:
171 Cooper Ave. Suite 110
Tonawanda, NY 14150 USA
Toll Free: 1-855-404-3193
Local: 1-716-877-7277
Fax: 1-866-331-3341

Rev Oct 11, 2018

info@watchnetaccess.com
www.watchnetaccess.com

INDIA:
RZ- 2, Ground Floor
Kapashera
Opp Kapashera Police Station
New Delhi-110037
Tel/Fax: +91 11 26816005

UAE:
PO Box 126312
No 703, Oxford Towers
Business Bay
Dubai, UAE
Tel: +971 4 2767117